MTCA.4 Fast Digitizer

+applications for LLRF systems @ DESY

Samer Bou Habib
ISE-WUT/DESY

Agenda

- Introduction
- DAMC-DS800 digitizer
- ADC measurements
- Applications
- Summary

Introduction

- Direct sampling of signals of frequencies ≥ 1.3 GHz
  - No DWC
  - No LO generation
- Very high sampling rates (>500 MSPS) ⇒ very low latencies
- Using undersampling to obtain information on amplitude, phase, and shape of signals
- Different Applications



DAMC-DS800

- AMC Fast Digitizer Card
- MTCA.4 Analog A1.1 class compliant
- 8 analog channels (AC or DC) up to 2.7GHz @ 800 MSPS 12-bit ADCs OR 4 channels @ 1600 MSPS
- 4 16-bit DACs up to 250 MSPS
- Very complex low noise/jitter CLK generation and distribution System
- Triggers, SRAM, communication interfaces…



DAMC-DS800


Zone 3 Connectors
Front Panel
AMC Backplane
ADC CLKs
DAC CLK
SYNC CLK
Input CLK
Output CLK
FCLK
TCLKA
TCLKB
RTM
RIO CLK
Jumpers
Jumpers
Jumpers
Jumpers
1:2
1:2
Distribution CLK
Ref1 for PLL
Ref2 for PLL
Reset CLK
Local Gen 10 MHz
Local Generation and Distribution
4:4 Cross point switch
Local Osc. 25 MHz
Local Osc. 25 MHz
PLL
PLL
ADCs
DACs
SRAMs
FPGA
PCIE (FPGA GTP)
FPGA GTP - LLL
FPGA GTP - LLL
FPGA GTP - LLL
FPGA GTP – 2xSFP + RTM_RIO

Sampling 1.3GHz at 780 MSPS



- SNR : ~55 dB
- ENOB : ~8.75

First ADC tests



Rms resolution from demodulation (10 MHz BW)		Rms resolution from demodulation (1 MHz BW)		Rms resolution from demodulation (100 kHz BW)	
Amplitude	Phase	Amplitude	Phase	Amplitude	Phase
0.0016%	0.077°	0.0013%	0.062°	0.0001%	0.0045°

ADC tests





Rms resolution from demodulation (10 MHz BW)		Rms resolution from demodulation (1 MHz BW)		Rms resolution from demodulation (100 kHz BW)	
Amplitude	Phase	Amplitude	Phase	Amplitude	Phase
0.0016%	0.077 °	0.0013%	0.062°	0.0001%	0.0045°

DAMC-DS800 + RTMs

Application examples:

Klystron life-time Management

High-Order Mode measurements (1.3/1.7/2.4GHz)

Femtosecond Fiberoptic Synchronisation



Klystron Lifetime Management

- Measurements of klystron parameters
- Detection of exceptional events
- Fast reaction to „abnormal" activity
- Tube recovery procedure according to detected event

⇒ Fast interlock and measurement system with reaction time < 250 ns

Klystron Lifetime Management





Applications – KLM/GP RTM

- 8 Channels
  - AC coupled: 400-2700 MHz BW
  - DC coupled: DC-2700 MHz BW
  - Possible filter implementation
- 2 x 8-bit ADC @ 250 MSPS
- 2 x 16-bit @ 10MSPS with very high ENOB >15 bits
- 2 Output channels (e.g. 2x VM) with RF-Gates
- Very Low Noise PLL and CLK distribution system
- For KLM: ADC + Calculations delay <55ns vs 168 ns in current system





High Order Modes Measurements

- Measurements of High Order Modes from couplers at cavities
- 3 frequencies filtered out:
  - 1.7 GHz – used for bpm and cavity allignment
  - 1.3 GHz – RF power
  - 2.4 GHz – from beam, for phase measurement w.r.t the 1.3 GHz

Applications – DRTM-HOM





- MTCA.4 A1.1 RTM designed
- 8 Channels each with a triple passband filter
- Very Low Noise PLL and CLK distribution system



Conclusion

- Very high speed AMC digitizer designed and being tested
- RTM designs/measurement in progress
- To be installed for LLRF (KLM and HOM)
- Implementations for other systems in progress

Thank you for your attention

S.BouHabib@elka.pw.edu.pl

samerbouhabib@desy.de